

# ***POWER SUPPLY 30V- 3Ax2 ZHAOXIN***

## ***Model: RXN-303DII***



### **Description:**

RXN Series are high precision, high stability and low ripple linear DC regulated power supply. The output voltage and output current between 0 to rated value is continuously adjustable. Constant voltage and constant current can automatic conversion.

### **Features:**

- Dual output, dual LED show voltage and current limit protection using current methods.
- Current limit can be adjusted to the plastic surface of the box, novel and beautiful appearance.

### **Application:**

Auto industry / Electronic industry / Communications industry / Digital product / Research Institutions / Educational Institutions

## *Specifications:*

- Input voltage: 110V  $\pm$  10% 50Hz ~ 60Hz
- Output voltage: 0-30V
- Output Current: 0-3A
- Output: Two independent outputs plus one fixed 5V/3A output
- Series: 0-60V ,0-3A
- Shunt: 0-30V ,0-6A
- Ripple and noise: 1mVrms (RMS)
- Load stability:  $\leq$  0.01% +2 mV
- Regulation accuracy:  $\leq$  0.01% +2 mV
- Display: LED digital display
- Display accuracy:  $\pm$  1%  $\pm$  1 word
- Output terminals: eight output terminals
- Protection: over-current protection
- Size: 343  $\times$  360  $\times$  170mm