

Wire Rope Clip

Toyolift Wire rope clip, is used to fix the loose end of the loop back to the wire rope. It usually consists of a U-shaped bolt, a forged saddle, and two nuts. The two layers of wire rope are placed in the U-bolt. The saddle is then fitted over the ropes on the bolt. The nuts secure the arrangement in place. Three or more clamps are usually used to terminate a wire rope.



Details

Parameters

WIRE ROPE CLIP- HOT DIP GALVANISED								
Rope	A	B	C	D	F	H	L	Weight
Dia inches	mm	mm	mm	mm	mm	mm	mm	Kgs/100
1/4	8	34	19	13	37	30	17	8
5/16	10	45	22	19	43	33	18	14
3/8	11	49	26	19	49	42	25	19
1/2	13	61	30	26	58	48	27	34
5/8	16	74	33	32	64	52	33	45
3/4	14	86	38	37	72	57	37	68
7/8	19	98	45	40	80	62	40	108
1	19	108	48	46	88	67	44	113
1 1/8	19	117	51	51	91	72	48	140
1 1/4	22	130	59	54	105	79	56	207
1 3/8	22	140	60	59	108	79	58	234
1 1/2	22	147	66	60	112	86	64	266
1 3/4	29	175	78	74	134	97	78	441
2	32	195	86	78	152	113	87	603
2 1/4	32	208	98	81	162	116	100	707
2 1/2	32	227	105	87	168	119	113	806
2 3/4	32	243	112	91	174	127	124	1,000
3	38	271	121	104	194	135	136	1,440